

Seppoman's SSM2164 PCB (work in progress...)

Parts List

| Part | Value | Reichelt No. |
|----------------|---------------|--------------|
| C1,C2 | 220 uF | RAD 220/25 |
| C3-C6 | 560 pF | KERKO 560P |
| C7-C12 | 100nF | Z5U-2,5 100N |
| C13-16 | 100pF | NPO-2,5 100P |
| C17-C20 | 470nF | Z5U-5 470N |
| IC1 | SSM2164PZ (*) | |
| IC2,IC3 | TL074 | TL 074 DIL |
| P1-P4 | 10k | 64W-10K |
| R1-R4, R9-R12, | 27k | METALL 27,0K |
| R17-R24 | 27k | |
| R5-R8 | 470 | METALL 470 |
| R13-R16 | 5.6k | METALL 5,60K |

Where to get the SSM2164

(*) There are quite a few places where you can buy the SSM2164, e.g. Farnell or Digikey usually have them on stock. Feel free to add your finds to this section :)

Value of C17..C20

These capacitors are part of a low pass filter that smoothes out noise/DAC steps etc from the CV input signal. There's a tradeoff between best cancellation of any zipper/background noise and a very snappy VCA on the other side. The value of 470nF stated in the parts list above is more on the "Silence" side of things. If you prefer a faster response of the VCA in return for some noise in certain situations, you can try lower values in this place. e.g. 220nF is a usable compromise, but you can go lower to 100nF, 10nF or even leave out the capacitor altogether. I suggest you might try out what suits you best with one single channel before stuffing all four caps.

From:

<http://www.midibox.org/dokuwiki/> - **MIDIbox**

Permanent link:

http://www.midibox.org/dokuwiki/doku.php?id=ssm2164_pcb&rev=1278686226

Last update: **2010/07/09 15:37**

