

# MIDIBox AY 3 8912 - PATCH MENU

Access the **PATCH MENU** via **F1**

## The Patch Menu:

LCD Menu			
LCD ROW	Func.	Data	Memo
1	NAME:	PATCH NAME	Edit the Patch Name here
2	NR :	0 to 127	Patch 0 = PIC internal Patch / 1 to 127 = Bankstick Patches
3	DO :	L W F	<b>L</b> oad Patch, <b>W</b> rite Patch, <b>F</b> ormat Bankstick1
4	status	(info)	

## Annotation:

- Bankstick = Bankstick1 by default
- A " !" before the [Patch Name] (@LCD ROW1) indicates, that the Patch is NOT loaded yet.
- The Fx Data is included (will be stored)

LCD ROW	EDIT	KEYS
1	NAME	Use A-Z, 0-9, SPACE = " _ ", after Patch Name Editing the user can delete the Patch Name via INST DEL key
2	Nr.	Use crsr ← → (+ / -)
3	Do	Use L W F
4	status	(info)

From:

<https://wiki.midibox.org/> - **MIDIbox**

Permanent link:

[https://wiki.midibox.org/doku.php?id=midibox\\_ay\\_patch\\_menu&rev=1258812474](https://wiki.midibox.org/doku.php?id=midibox_ay_patch_menu&rev=1258812474)

Last update: **2009/11/21 14:07**

