


MB SEQ functions - quick reference

Detailed info for options and functions is available at

http://www.ucapps.de/midibox_seq_manual_m.html

Print-friendly (on two A4 sheets) xls version available here [mbseq_prn_.zip](#)

#	Function	Description / Options															
Dedicated button functions (these can vary depending on panel design and MBSEQ_HW.V4 file)																	
1	Pattern 1,2,3,4	Select pattern/track group - G1, G2, G3, G4															
2	Track 1,2,3,4	Select track within track group - T1, T2, T3, T4. 16 tracks are available in total															
3	Trigger layer A,B,C	Select trigger layer A or B or C. Holding C opens trigger layer selection menu and allows to select others <html>	Gate	Acc	Roll	Glide	Skip	R.G(random gate)	R.V(random value)	No FX	</html>						
4	Parameter layer A,B,C	Select parameter layer A and B. C switches between C & D or with <i>Press&Hold</i> open parameter layer selection menu and to select others. Four parameter layers available by default, but CC, Pitch, Prob, Delay can be added via trigger selection menu (?)  <html>	Note	Vel	Length	Roll	</html>										
5	Step View	View and select steps if more than 16 are used <html>	1..16	17..32	...etc</html>												
6	Pattern	Select/load pattern/track group G1, G2, G3, G4 from SD memory location															
7	Song	Select song parameters <html>	Song #	Position	Action{Stop; x1..x16; Jump Pos; Jump Song; Mixer; Tempo; Mutes}	Select patterns: G1,G2,G3,G4	</html>										
8	Edit	Enter edit mode to edit parameter layer step values and set trigger layer steps															
9	Mute	Quickly mute/unmute tracks 1..16															
10	Solo	Solo current track															
11	←/→ (Left/Right)	Move cursor position. <i>Left</i> has limited usage															
12	+/- (Inc/Dec)	Same as <i>Jog Dial</i> encoder - increases/decreases the current value															
13	Exit	Quickly exit to top menu															

#	Function	Description / Options																		
14	Select	(Press&Hold) Select steps to be controlled by <i>All</i> function. Obviously has usage in other situations as well (which?) 																		
15	All	Edit all selected steps set with <i>Select</i> function																		
16	Copy	Copy steps from selected # to #. Step # can be edited by <i>Select</i> function																		
17	Paste	Paste copied steps starting from # step. Step # can be edited by <i>Select</i> function																		
18	F1 (Clear)	(Press&Hold) Wipe selected track. Other functions can be assigned in MBSEQ_HW.V4 file																		
19	F2 (Select track)	(Press&Hold) Select track. Other functions can be assigned in MBSEQ_HW.V4 file																		
20	F3 (Select parameter layer)	(Press&Hold) Select parameter layer A,B,C,D...etc. Other functions can be assigned in MBSEQ_HW.V4 file																		
21	F4 (Select trigger layer)	(Press&Hold) Select/assign trigger layer 1..8. Other functions can be assigned in MBSEQ_HW.V4 file																		
22	Rec	Open record menu <html>	Track #	Record{Live; Step}	Mode{Mono; Poly}	AStart{on; off}	Step #	TglGate		Port #	Chn #	</html>								
23	«	Rewind. Active only in song mode																		
24	Stop	Stop playback and reset position to beginning																		
25	Play	Start playback of patterns/song																		
26	Pause	Halt/resume playback																		
27	»	Forward. Active only in song mode																		
28	Metronome	Toggle metronome on/off																		
29	Fast	Activate <i>Fast</i> mode for quicker value selection with encoders. Speed options for <i>Fast</i> can be changed in MBSEQ_HW.V4 file																		
30	Scrub	(Press&Hold) + Jog Wheel dynamically change actual position																		
Menu functions																				

From:
<https://wiki.midibox.org/> - **MIDIbox**

Permanent link:
https://wiki.midibox.org/doku.php?id=midibox_seq_quick_reference&rev=1273425081

Last update: **2010/05/09 17:11**

