Changing DOUT pins in mbSID v2

1/5

Overview

2024/04/25 13:24

If you're like me, you'd rather change the software mapping of the output (LED) pins than wire everything according to the original schematic - which may not even be possible due to differences in the CS. This HowTo will demonstrate one of the many ways to change the mapping according to your own wiring. This HowTo is only meant to change LEDs which are connected to individual pins. With LEDs connected as a matrix this will not work.

Difficulty level:

• easy ₀₋₁₋₂₋₃.**4**.5-6-7-8-9 hard

Required actions:

- Search/manually edit
- Install other software
- Compile

Affected files [1]:

• setup_*.asm

Required software:

http://www.ucapps.de/mios/dout_buttons_v1_3a.zip

Step-by-Step description

1. Finding the correct pins

- Download the dout_buttons_v1_3a application. This application lights one LED at a time and displays its SR and pin number.
- Install it on the (master) core
- Power up the core. Your dispay should now show sth. like this

Digital Out Test

```
SR# 1 Pin#0 0x00
```

• Upon pressing a button which is connected to an odd pin the program will increase number of the pin to power. Pressing the button once will display this:

Digital Out Test SR# 1 Pin#1 0x01

- Pressing a button which is connected to an even pin will decrease the number of the pin to power.
- Toggle through the pins and SRs and write down the SR# and Pin# for every LED until all of your leds have been lit.
- At this point you know have all the SR# and Pin# for all the LEDs

2. Changin the source code

- Open setup_*.asm
- Find the table called CS_MENU_DOUT_TABLE which looks like this:

CS_MENU_DOUT_TABL	.E					
;; Reg	gister and bit	SR#	Pin#	D	escri	ption
	CS_MENU_SELECTED_SI			1,		; SID1
) is the D7 output of					
	CS_MENU_SELECTED_SI	D_FLAGS, 1,		1,	1	,
SID2 LED				-	-	
	CS_MENU_SELECTED_SI	D_FLAGS, 2,		1,	2	;
SID3 LED DOUT ENTRY	CS_MENU_SELECTED_SI			1,	3	,
SID4 LED	C2_MENU_SELECTED_ST	$D_{\text{FLAUS}}, 5,$		τ,	5	;
JID4 LLD						
DOUT ENTRY	CS MENU MODE, ,	1,	4	; Sh	ift L	ED
DOUT_ENTRY	CS MENU MODE, 1,			; (
DOUTENTRY	CS MENU MODE, 4,			; E		
_						
DOUT_ENTRY	CS_MENU_SELECTED_OS	C_FLAGS, ,		2,		; OSC1
LED						
DOUT_ENTRY	CS_MENU_SELECTED_0S	C_FLAGS, 1,			1	;
DOUT_ENTRY OSC2 LED		_		2,	1	
DOUT_ENTRY OSC2 LED DOUT_ENTRY	CS_MENU_SELECTED_OS	_			1	
DOUT_ENTRY OSC2 LED		_		2,	1	
DOUT_ENTRY OSC2 LED DOUT_ENTRY OSC3 LED	CS_MENU_SELECTED_0S	_ C_FLAGS, 2,		2, 2,	1 2	;
DOUT_ENTRY OSC2 LED DOUT_ENTRY OSC3 LED DOUT_ENTRY	CS_MENU_SELECTED_OS	C_FLAGS, 2, 2, 3	;	2, 2, 0SC En	1 2 IV LED	;
DOUT_ENTRY OSC2 LED DOUT_ENTRY OSC3 LED	CS_MENU_SELECTED_0S	_ C_FLAGS, 2,	; ;	2, 2, 0SC En	1 2 NV LED lisc L	; ED
DOUT_ENTRY OSC2 LED DOUT_ENTRY OSC3 LED DOUT_ENTRY DOUT_ENTRY	CS_MENU_SELECTED_OS TMP1, , TMP1, 1,	_ C_FLAGS, 2, 2, 3 2, 4	; ;	2, 2, 0SC En 0SC M	1 2 NV LED lisc L	; ED
DOUT_ENTRY OSC2 LED DOUT_ENTRY OSC3 LED DOUT_ENTRY DOUT_ENTRY DOUT_ENTRY DOUT_ENTRY	CS_MENU_SELECTED_OS TMP1, , TMP1, 1,	_ C_FLAGS, 2, 2, 3 2, 4	;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;	2, 2, OSC En OSC M OSC A	1 2 NV LED Lisc L Ssign	; ED LED
DOUT_ENTRY OSC2 LED DOUT_ENTRY OSC3 LED DOUT_ENTRY DOUT_ENTRY DOUT_ENTRY	CS_MENU_SELECTED_OS TMP1, , TMP1, 1, TMP1, 2,	C_FLAGS, 2, 2, 3 2, 4 2, 5	;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;	2, 2, OSC En OSC M OSC A OSC Tr	1 2 NV LED Lisc L Ssign riangl	; ED LED e LED

2024/04/25 13:24	3/5			Changing DOUT pins in mbSID v2
DOUT_ENTRY DOUT_ENTRY	TMP1, 6, TMP1, 7,	3, 3,	2 3	,
DOUT_ENTRY	TMP2, ,			; OSC Sync LED
DOUT_ENTRY	TMP2, 1,			; OSC Ring LED
DOUT_ENTRY	TMP3, , TMP3, 1,	3, 3,	4	; Filter O1 LED ; Filter O2 LED
DOUT_ENTRY				,
DOUT_ENTRY	TMP3, 2,			; Filter 03 LED
DOUT_ENTRY	TMP3, 3,	3,	/	; Filter Ext LED
DOUT_ENTRY		4,		/ -
DOUT_ENTRY		4,		; Filter BP LED
DOUT_ENTRY	TMP3, <u>6</u> ,	4,		; Filter HP LED
DOUT_ENTRY	TMP3, 7,	4,	3	; Filter 30 LED
DOUT_ENTRY	TMP2, 4,	4,	4	; ENV1 LED
DOUT_ENTRY	TMP2, 5,	4,	5	; ENV2 LED
DOUT_ENTRY	TMP2, 6,	4,	6	; ENV Ctrl LED
DOUT_ENTRY	TMP2, 7,	4,	7	; ENV Assign LED
DOUT_ENTRY	TMP4, ,	5,		; LF01 LED
DOUT ENTRY	TMP4, 1,	5,	1	; LFO2 LED
DOUT_ENTRY	TMP4, 2,	5,		; LFO3 LED
DOUTENTRY	TMP4, 3,	5,		; LFO4 LED
DOUTENTRY	TMP4, 4,			; LF05 LED
DOUT_ENTRY	TMP4, 5,	5,	5	
DOUT ENTRY	TMP5, ,	5,	6	; LFO Sine LED
DOUTENTRY				; LFO Triangle LED
DOUT ENTRY		6,		; LFO Saw LED
DOUT ENTRY				; LFO Pulse LED
DOUT_ENTRY				; LFO Random LED
;; o Play LE ;; o Mode Me ;; o Mode Ma	l LED functions which D (TMP5, 6) ter LED (TMP2, 2) trix LED (TMP2, 3) ED (TMP4, 6)	n could be	add	ed:
	ED (TMP4, 7)			
	itive LED (TMP5, 5)			

```
;; don't remove this "end-of-table" entry!
DOUT_ENTRY_EOT
```

- All you need to change is the 4th and 5th column (SR# and Pin#)
- I usually set all SR# and Pin# to 0 before changing anything that way it's hard to miss anything and it keeps you from having doubles if you do not use of the buttons
- Go through the list you've made earlier and change the Pin# and SR# according to it for each

LED.

• If there are LEDs you don't have on your CS just comment out that line by adding ;; (two semicolons) to the beginning of that line. Like this:

;; this LED will work DOUT_ENTRY CS_MENU_MODE, ,	1, 4	r F	Shift LED	
;; this LED has been removed by comment;; DOUT_ENTRY CS_MENU_MODE, 0,	0	4	; Shift LED	

• Done with the LEDs

3. (Optional) Additional predefined LEDs

- If you want to use any of the predefined LEDs that are commented out by default this is how to do it.
- At the end of the CS_MENU_DOUT_TABLE you'll find this

```
;; additional LED functions which could be added:
;; o Play LED (TMP5, 6)
;; o Mode Meter LED (TMP2, 2)
;; o Mode Matrix LED (TMP2, 3)
;; o SID L LED (TMP4, 6)
;; o SID R LED (TMP4, 7)
;; o LFO Positive LED (TMP5, 5)
```

 Those LEDs are predefined but not used. To use them just add a line to the table. Let's say we want the "Play LED"

;; o Play LED (TMP5, 6)

 Remove the ;; and the parentheseses and replace the name ("Play LED") by DOUT_ENTRY giving you this:

;; DOUT_ENTRY TMP5, 6

• Now add ", " + SR# + ", " + Pin# giving you sth like this:

;; DOUT_ENTRY TMP5, 6, 4, 7

• This would already work but it's a good idea to add a comment to it so you remember what this LED does:

;; DOUT_ENTRY TMP5, 6, 4, 7 ;; Play LED - whee!

• Done with the extra LEDs

×

4. Recompile

- Now recompile the setup_*.asm
- Send it to your mbSID via MIOSStudio
- You're all done!

From: http://wiki.midibox.org/ - **MIDIbox**

Permanent link: http://wiki.midibox.org/doku.php?id=changing_dout_pins&rev=1203710298

Last update: 2009/10/22 14:13