2019/05/27 20:33 1/3 wCoreF4 PCB


# wCoreF4 PCB

This is the carrier board for the Waveshare Core407v. It performs breakout functions of all of the standard ports as per the design based on the STM32 Discovery.

### **Schematic**


The circuit is mostly identical to what was drawn previously. The following parts are different:

#### **USB** entry (J1)




This header supplies +5V, 0V, USB data and the ID state. Normally it will be connected to the USB module by a short cable.

#### Extended port (J16E)



The original J16 functionality is preserved, but extra pins are available on a IDC16 header. These include the Reset signal and pins normally controlling LEDs. This header is normally connected to the RES-SD module.

### **User button (JPA0)**



This jumper replaces the "bootloader" functionality of the Discovery board's blue button. It could be wired to an external panel control if needed.

## **BOM v1.0**

Type	Qty	Value	Package	Parts	Mouser	Reichelt	Conrad	Other	Notes		
Resistors											
	2	220R 5%	THT	R7A, R8A							
	2	220R 5%	1206	R7B, R8B							
	1	330R 5%	THT	R102							
	4	1k 5%	1206	R7B1-4							
	2	1k 5%	THT	R11, R13							
	1	10k 5%	THT	R12							
	1	220k 5%	THT	R101							
Pots											
	2	10k	6*5mm vert	P1, P2							
Capacitors											
	3	100n	1206	C1A, C1B, C2							
					Diodes						
	1	1N4148	THT								
		•		Tr	ansistors						
	1	BC337	TO-92	T1							
ICs											
	2	74HCT125	SOIC	IC1A, IC1B	595-SN74HCT125DR				Ensure <b>HCT</b>		
	1	74HC595	SOIC	IC2							
Headers											
	2	1*2	male								

http://wiki.midibox.org/ Printed on 2019/05/27 20:33

Type	Qty	Value	Package	Parts	Mouser	Reichelt	Conrad	Other	Notes		
Resistors											
	1	1*3	male								
	1	1*5	male						or wire directly		
	9	2*5	male								
	3	2*8	male								
	2	2*8	male								
Hardware											
	4		M3 spacer	8mm(?)							
MCU breakout											
	1	Waveshare Core 407v									

## **Versions**

v1.0: first release.

# **Assembly**

#### License

Currently the design is  $\ \odot$  2016 antilog devices with all rights reserved; all documentation is CC BY-NC-SA 3.0.

From:

http://wiki.midibox.org/ - MIDIbox

Permanent link:

http://wiki.midibox.org/doku.php?id=wcoref4\_pcb&rev=1504733265

Last update: **2017/09/06 22:27** 

