

### MIOS DIN/DOU Pin Numbers

Sometimes the pin numbers of special DINs or DOUTs can be specified in the main.asm or setup\_\*.asm file of a MIOS application.

Examples:

```
#define DEFAULT_MIDI_RX_LED 0x40 ; DOUT SR#9, pin D0
#define DEFAULT_MIDI_TX_LED 0x41 ; DOUT SR#9, pin D1
```

or

```
#define DEFAULT_DIN_MENU_EXEC 7 ; menu exec button assigned to
DIN pin #7
#define DEFAULT_DIN_MENU_SNAPSHOT 6 ; menu snapshot button
assigned to DIN pin #4
#define DEFAULT_DIN_MENU_RIGHT 5 ; NOT USED - overlaid by
datawheel
#define DEFAULT_DIN_MENU_LEFT 4 ; NOT USED - overlaid by
datawheel
```

or

```
;; SR Pin Mode
ENC_ENTRY 5, 0, MIOS_ENC_MODE_NON_DETENTED ; V-Pot 1
ENC_ENTRY 5, 2, MIOS_ENC_MODE_NON_DETENTED ; V-Pot 2
ENC_ENTRY 5, 4, MIOS_ENC_MODE_NON_DETENTED ; V-Pot 3
ENC_ENTRY 5, 6, MIOS_ENC_MODE_NON_DETENTED ; V-Pot 4
```

The following table should give you a quick overview over the numbers. Please bear in mind that we are sometimes counting from 0, and sometimes from 1.

Means: sometimes the first pin or shiftregister has number 0, sometimes it has number 1 - thats always an issue, because programmer mostly prefer to count from 0, users want to count from 1 - it's a bit of a mess! Forgive me! 😊

In the meantime I've tried to make the setup more consistent. Shiftregisters are always counted from 1, and pins are always counted from 0

Important Note: for DIN shift registers, pins will be reflected on software- level in reversed order for each shift register:

D7 (hardware level) of the first shift register will be pin-number 0 (software level), not 7! D0 (hardware level) of the second shift register will be pin-number 15 (software level), not 8! The first shift register is for both DIN and DOUT the one that is closest to the core on hardware level.

In the datasheets of the shift-register IC's, D0 is often labled A / QA, D7 is labled H / QH.

Note that this applies only for DIN's, NOT for DOUT's. For DOUT's D0 / A (hardware) will be the lowest pin number in software.

DIN chain hardware-level: CORE → R1::qH → R1::H → R1 → R1::G ..... R2::qH → R2::H etc. DOUT chain hardware-level: CORE → R1::SER → R1::A → R1::B → R1::C ..... R2::SER → R2::A etc.

If you want to read more about this, refer this forum discussion:  
<http://www.midibox.org/forum/index.php/topic,12379.0.html>

See also the following table to get a clearer picture.

Ok, here the table:

| Shift Register | SR number | Pin Name DOUT PCB | Pin Number | Hex number |
|----------------|-----------|-------------------|------------|------------|
| first          | 1         | D0                | 0          | 0x00       |
| first          | 1         | D1                | 1          | 0x01       |
| first          | 1         | D2                | 2          | 0x02       |
| first          | 1         | D3                | 3          | 0x03       |
| first          | 1         | D4                | 4          | 0x04       |
| first          | 1         | D5                | 5          | 0x05       |
| first          | 1         | D6                | 6          | 0x06       |
| first          | 1         | D7                | 7          | 0x07       |
| second         | 2         | D0                | 8          | 0x08       |
| second         | 2         | D1                | 9          | 0x09       |
| second         | 2         | D2                | 10         | 0x0a       |
| second         | 2         | D3                | 11         | 0x0b       |
| second         | 2         | D4                | 12         | 0x0c       |
| second         | 2         | D5                | 13         | 0x0d       |
| second         | 2         | D6                | 14         | 0x0e       |
| second         | 2         | D7                | 15         | 0x0f       |
| third          | 3         | D0                | 16         | 0x10       |
| third          | 3         | D1                | 17         | 0x11       |
| third          | 3         | D2                | 18         | 0x12       |
| third          | 3         | D3                | 19         | 0x13       |
| third          | 3         | D4                | 20         | 0x14       |
| third          | 3         | D5                | 21         | 0x15       |
| third          | 3         | D6                | 22         | 0x16       |
| third          | 3         | D7                | 23         | 0x17       |
| fourth         | 4         | D0                | 24         | 0x18       |
| fourth         | 4         | D1                | 25         | 0x19       |
| fourth         | 4         | D2                | 26         | 0x1a       |
| fourth         | 4         | D3                | 27         | 0x1b       |
| fourth         | 4         | D4                | 28         | 0x1c       |
| fourth         | 4         | D5                | 29         | 0x1d       |

| Shift Register | SR number | Pin Name DOUT PCB | Pin Number | Hex number |
|----------------|-----------|-------------------|------------|------------|
| fourth         | 4         | D6                | 30         | 0x1e       |
| fourth         | 4         | D7                | 31         | 0x1f       |
| fifth          | 5         | D0                | 32         | 0x20       |
| fifth          | 5         | D1                | 33         | 0x21       |
| fifth          | 5         | D2                | 34         | 0x22       |
| fifth          | 5         | D3                | 35         | 0x23       |
| fifth          | 5         | D4                | 36         | 0x24       |
| fifth          | 5         | D5                | 37         | 0x25       |
| fifth          | 5         | D6                | 38         | 0x26       |
| fifth          | 5         | D7                | 39         | 0x27       |
| sixth          | 6         | D0                | 40         | 0x28       |
| sixth          | 6         | D1                | 41         | 0x29       |
| sixth          | 6         | D2                | 42         | 0x2a       |
| sixth          | 6         | D3                | 43         | 0x2b       |
| sixth          | 6         | D4                | 44         | 0x2c       |
| sixth          | 6         | D5                | 45         | 0x2d       |
| sixth          | 6         | D6                | 46         | 0x2e       |
| sixth          | 6         | D7                | 47         | 0x2f       |
| seventh        | 7         | D0                | 48         | 0x30       |
| seventh        | 7         | D1                | 49         | 0x31       |
| seventh        | 7         | D2                | 50         | 0x32       |
| seventh        | 7         | D3                | 51         | 0x33       |
| seventh        | 7         | D4                | 52         | 0x34       |
| seventh        | 7         | D5                | 53         | 0x35       |
| seventh        | 7         | D6                | 54         | 0x36       |
| seventh        | 7         | D7                | 55         | 0x37       |
| eighth         | 8         | D0                | 56         | 0x38       |
| eighth         | 8         | D1                | 57         | 0x39       |
| eighth         | 8         | D2                | 58         | 0x3a       |
| eighth         | 8         | D3                | 59         | 0x3b       |
| eighth         | 8         | D4                | 60         | 0x3c       |
| eighth         | 8         | D5                | 61         | 0x3d       |
| eighth         | 8         | D6                | 62         | 0x3e       |
| eighth         | 8         | D7                | 63         | 0x3f       |
| ninth          | 9         | D0                | 64         | 0x40       |
| ninth          | 9         | D1                | 65         | 0x41       |
| ninth          | 9         | D2                | 66         | 0x42       |
| ninth          | 9         | D3                | 67         | 0x43       |
| ninth          | 9         | D4                | 68         | 0x44       |
| ninth          | 9         | D5                | 69         | 0x45       |
| ninth          | 9         | D6                | 70         | 0x46       |
| ninth          | 9         | D7                | 71         | 0x47       |
| tenth          | 10        | D0                | 72         | 0x48       |
| tenth          | 10        | D1                | 73         | 0x49       |

| <b>Shift Register</b> | <b>SR number</b> | <b>Pin Name DOUT PCB</b> | <b>Pin Number</b> | <b>Hex number</b> |
|-----------------------|------------------|--------------------------|-------------------|-------------------|
| tenth                 | 10               | D2                       | 74                | 0x4a              |
| tenth                 | 10               | D3                       | 75                | 0x4b              |
| tenth                 | 10               | D4                       | 76                | 0x4c              |
| tenth                 | 10               | D5                       | 77                | 0x4d              |
| tenth                 | 10               | D6                       | 78                | 0x4e              |
| tenth                 | 10               | D7                       | 79                | 0x4f              |
| eleventh              | 11               | D0                       | 80                | 0x50              |
| eleventh              | 11               | D1                       | 81                | 0x51              |
| eleventh              | 11               | D2                       | 82                | 0x52              |
| eleventh              | 11               | D3                       | 83                | 0x53              |
| eleventh              | 11               | D4                       | 84                | 0x54              |
| eleventh              | 11               | D5                       | 85                | 0x55              |
| eleventh              | 11               | D6                       | 86                | 0x56              |
| eleventh              | 11               | D7                       | 87                | 0x57              |
| twelfth               | 12               | D0                       | 88                | 0x58              |
| twelfth               | 12               | D1                       | 89                | 0x59              |
| twelfth               | 12               | D2                       | 90                | 0x5a              |
| twelfth               | 12               | D3                       | 91                | 0x5b              |
| twelfth               | 12               | D4                       | 92                | 0x5c              |
| twelfth               | 12               | D5                       | 93                | 0x5d              |
| twelfth               | 12               | D6                       | 94                | 0x5e              |
| twelfth               | 12               | D7                       | 95                | 0x5f              |
| thirteenth            | 13               | D0                       | 96                | 0x60              |
| thirteenth            | 13               | D1                       | 97                | 0x61              |
| thirteenth            | 13               | D2                       | 98                | 0x62              |
| thirteenth            | 13               | D3                       | 99                | 0x63              |
| thirteenth            | 13               | D4                       | 100               | 0x64              |
| thirteenth            | 13               | D5                       | 101               | 0x65              |
| thirteenth            | 13               | D6                       | 102               | 0x66              |
| thirteenth            | 13               | D7                       | 103               | 0x67              |
| fourteenth            | 14               | D0                       | 104               | 0x68              |
| fourteenth            | 14               | D1                       | 105               | 0x69              |
| fourteenth            | 14               | D2                       | 106               | 0x6a              |
| fourteenth            | 14               | D3                       | 107               | 0x6b              |
| fourteenth            | 14               | D4                       | 108               | 0x6c              |
| fourteenth            | 14               | D5                       | 109               | 0x6d              |
| fourteenth            | 14               | D6                       | 110               | 0x6e              |
| fourteenth            | 14               | D7                       | 111               | 0x6f              |
| fifteenth             | 15               | D0                       | 112               | 0x70              |
| fifteenth             | 15               | D1                       | 113               | 0x71              |
| fifteenth             | 15               | D2                       | 114               | 0x72              |
| fifteenth             | 15               | D3                       | 115               | 0x73              |
| fifteenth             | 15               | D4                       | 116               | 0x74              |
| fifteenth             | 15               | D5                       | 117               | 0x75              |

| Shift Register | SR number | Pin Name DOUT PCB | Pin Number | Hex number |
|----------------|-----------|-------------------|------------|------------|
| fifteenth      | 15        | D6                | 118        | 0x76       |
| fifteenth      | 15        | D7                | 119        | 0x77       |
| sixteenth      | 16        | D0                | 120        | 0x78       |
| sixteenth      | 16        | D1                | 121        | 0x79       |
| sixteenth      | 16        | D2                | 122        | 0x7a       |
| sixteenth      | 16        | D3                | 123        | 0x7b       |
| sixteenth      | 16        | D4                | 124        | 0x7c       |
| sixteenth      | 16        | D5                | 125        | 0x7d       |
| sixteenth      | 16        | D6                | 126        | 0x7e       |
| sixteenth      | 16        | D7                | 127        | 0x7f       |

From:

<https://wiki.midibox.org/> - **MIDIbox**

Permanent link:

[https://wiki.midibox.org/doku.php?id=din\\_dout\\_pintable&rev=1227452597](https://wiki.midibox.org/doku.php?id=din_dout_pintable&rev=1227452597)

Last update: **2008/11/23 15:03**

